

SENSOR RESISTANCE VS TEMPERATURE AUTO COOL CONTROLLERS

SENSOR LEADS MUST NOT BE SHORTED
TO THE BRASS SHIM! SHOULD BE OPEN.

100 F	27.6K
110 F	22.5K
120 F	17.5K
130 F	14.2K
140 F	11.7K
150 F	9.3K
160 F	7.7K
170 F	6.2K
180 F	5.2K
190 F	4.4K
200 F	3.6K

RADIO RESEARCH, LTD.
WWW.AUTOCOOLGUY.COM
autocoolguy@yahoo.com
562-367-3225